



The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.

Signed

Dated 7 FEB 2001

**CERTIFIED COPY OF
PRIORITY DOCUMENT**

Patents Form 1/77

Patents 1977
(Rule 16)


The
Patent
Office

1/77

25APR00 EST 174-3 100068
P01/7700 000-009945.7
Gwent NP9 1RH

Request for grant of a patent

(See the notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)



20 APR 2000

1. Your reference

2. Patent application number
(The Patent Office will fill in this part)

0009945.7

3. Full name, address and postcode of the or of each applicant (underline all surnames)

STMicroelectronics Limited
1000 Aztec West,
Almondsbury
Bristol BS12 4SQ

Patents ADP number (*if you know it*)

7460272001

If the applicant is a corporate body, give the country/state of its incorporation

United Kingdom

4. Title of the invention

DEBUGGING DEVICE AND METHOD

5. Name of your agent (*if you have one*)

Page White & Farrer

"Address for service" in the United Kingdom to which all correspondence should be sent (*including the postcode*)

54 Doughty Street
London WC1N 2LS

Patents ADP number (*if you know it*)

1255003

6. If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications and (*if you know it*) the or each application number

Country

Priority application number
(*if you know it*)

Date of filing
(*day / month / year*)

None

7. If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application

Number of earlier application

Priority application number
(*if you know it*)

Date of filing
(*day / month / year*)

8. Is a statement of inventorship and of right to grant of a patent required in support of this request? (*Answer 'Yes' if:*
a) any applicant named in part 3 is not an inventor, or
b) there is an inventor who is not named as an applicant, or
c) any named applicant is a corporate body
See note (d))

YES

9. Enter the number of sheets for any of the following items you are filing with this form. Do not count copies of the same document

Continuation sheets of this form 0

Description 14

Claim(s) 3

Abstract 0

Drawing(s) 4 + 4

10. If you are also filing any of the following, state how many against each item.

Priority documents N/R

Translations of priority documents N/R

Statement of inventorship and right to grant of a patent (Patents Form 7/77) 1

Request for preliminary examination and search (Patents Form 9/77) 0

Request for substantive examination (Patents Form 10/77) 0

Any other documents (please specify)

11. I/We request the grant of a patent on the basis of this application.

Signature

Date 20/04/00

PAGE WHITE & FARRER

12. Name and daytime telephone number of person to contact in the United Kingdom W J Neobard 0171-831-7929

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

- If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.
- Write your answers in capital letters using black ink or you may type them.
- If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.
- If you have answered 'Yes' Patents Form 7/77 will need to be filed.
- Once you have filled in the form you must remember to sign and date it.
- For details of the fee and ways to pay please contact the Patent Office.

DEBUGGING DEVICE AND METHOD

The present invention relates to a method of and device for debugging a target computer.

During development and testing of an embedded computer system, especially an embedded microprocessor-based computer system, it is normally necessary to connect the system to a host computer so that an engineer can debug the embedded system. Debugging software on the host computer provides access by the engineer into the embedded system. Typically, the engineer uses the host computer and debugging software to set break points which stop threads of execution on the target embedded system, monitor registers in the target, monitor memory states and monitor input and output data. The engineer may also restart threads that have been previously stopped and perform a variety of other tasks including rebooting the target computer using the host.

Although in normal operation the embedded system may be virtually self-sufficient in that it does not in normal use need to perform input/output, it may be necessary during debugging for such input/output to be performed. Examples of this are displaying messages at the host, reading characters from the host keyboard or reading data from a file stored on the host.

Similar situations requiring input/output may occur where an embedded system is sold to an end user and the end user needs to customize the embedded system, for example writing information into programmable read only memory in the embedded system.

Embedded systems may contain more than one application, for instance stored in a read only memory or downloaded over a link, at run-time. An example of the latter is a satellite transmission link. Each such application may need to perform input/output of data to the host computer during debugging. Furthermore, applications may be interconnected so that one application that is executing may, at a virtually arbitrary point in time, cause another application to start executing. Although it is possible to provide input/output libraries during the construction of each application, such libraries, and as a result the protocol implemented by the application for input/output, may differ between applications.

It is proposed in a related application to provide a dynamically loaded library containing routines necessary for communication. Such a library may additionally or alternatively include other routines, for example subroutines that allow hardware bugs discovered during debugging to be masked or worked around. A mechanism is also proposed in a related application to allow an application to locate the dynamic library by means of the stack of an exception handler for that application.

Typically, each application may be built individually, with a linker dynamically determining the addressable locations used for protocol implementation. If there is more than one application needing to access the library, the host will not be able to determine easily which memory locations should be used at a particular point in time. It would of course be possible to arrange a system which reserved locations in memory for protocol use but this requires application developer intervention regarding the input/output implementation.

As used herein, the term 'digital signal processor' includes microprocessors in general and other like digitally operating processing devices.

It is accordingly a primary object of the present invention to at least partially overcome the difficulties of the prior art.

According to the present invention there is provided a method of debugging a target system using a host system connected thereto, the target system comprising a digital signal processor having associated memory, said memory including a reserved storage location designated as a vector, said memory further storing plural application programs, each application program having respective associated exception handler code, the method comprising:

- dynamically loading a stack to said reserved region;

- causing the vector of said target system to point to said stack whereby all said applications use the said stack for said exception.

According to a second aspect of the invention there is provided a device for debugging a target system, the device comprising a host system connected thereto, the target system comprising a digital signal processor having associated memory comprising plural addressable locations, said target system further having a reserved storage location designated as a vector, said memory further storing plural application programs, each application program having respective associated exception handler code, the device further comprising:

- stack dynamic loading circuitry in said host for dynamically loading a stack to said reserved region, whereby said loader comprises an indication of the location in said memory of said stack;

vector writing circuitry receiving said indication, and writing to said the vector of said target system the address of said stack whereby all said applications use the said stack for said exception.

The invention will now be described with reference to the accompanying drawings in which:-

Figure 1 shows a block diagram of a host computer connected to a target computer for downloading an input/output library;

Figure 2 shows a schematic partial view of the target system showing the use of a pointer to indirectly access an entry point of a dynamically loaded library;

Figure 3 shows a block diagram of a target computer showing how data communication is effected using the invention;

Figure 4 shows a schematic partial view of the target system showing an alternative way of accessing an entry point of a dynamically loaded library.

In the various figures like reference numerals refer to like parts.

Referring first to Figure 1, a host computer 1 includes an input device such as a keyboard 2 and runs debugging software 4 for a target embedded system 100, the host and target being connected via a communications link 101, 102. This link is shown figuratively in Figure 1 as two separate paths with a first path 101 conveying data from the host machine 1 to the target machine 100 and a second path 102 connecting to the target computer 100 to the host computer 1. It will be understood that the link may be of any conventional type that allows two-way communication. Such communication need not be simultaneous. The target system typically includes a

microprocessor or other processing circuitry, hereinafter referred to as a digital signal processor.

The host computer further includes a file 3, hereinafter referred to as a library, containing a collection of subroutines and information that will be used by the target computer to implement a multilayered communication protocol over the physical link 101, 102.

The link 101 outgoing from the host computer 1 to the target computer 100 is shown figuratively as connected to four portions of the target system, namely a first application 121, a second application 122, a block 123 whereby the embedded digital signal processor of the target system 100 may be reset, and to the volatile memory 200 of the target system.

It will be understood by those skilled in the art that the debugging software 4 may communicate over the link 101 to interrogate or monitor the registers in the target, the memory in the target, to stop and restart threads of execution.

The applications 121, 122 may be stored in read only memory or may be downloaded via a separate link (not shown) at run-time, e.g. into RAM 200.

Referring to Figure 2, the target system 100 includes an exception handler 20 loaded into a memory area 201, the exception handler 20 having a stack 21 in a reserved area of memory 202, the stack including a reserved location 205. In the embodiment described, which has a negative-growing stack, the reserved location 205 is selected as the bottom of the stack. The host system 1 may dynamically load the exception handler stack into the target memory. The target includes a hard-wired location

190 accessible to both the target and the host, hereinafter referred to as a vector.

As used in this document, a vector is a reserved area, typically at a hard-wired location, used to contain address data of a key system entity. A pointer is a general holder of the address of a selected (arbitrary) entity.

At the start of debugging, the library 3 is accessed by the linker-loader 120 of the host. The linker-loader dynamically loads the library to a suitable vacant area of memory 203 of the target. As known to the skilled person, this location is determined in dependence on the usage of memory by applications, data and functions. The result is a loaded library 30 having an entry point 204 within the region of memory 203. At the time of loading the library 30 into memory, the linker-loader 120 determines where in the memory of the target to load the stack. The linker-loader stores at the bottom stack location 205, hereinafter referred to as the entry point pointer, information representing the entry point 204 and loads the location of the stack into the vector 190. It will be understood by those skilled in the art that the information stored by the vector 190 may be of various forms, including the absolute address of the exception handler stack 202 or other information such as an offset.

If the embedded system 100 is not connected to a host, no library will have been loaded and entry point pointer 205 is set to contain a predetermined value indicative of the fact that no library is available, as will be described below. This predetermined value may be a value that is not a valid address.

When an application performs input/output, the following events take place:-

1. The application identifies the need to perform input/output, and calls a linked-in function setting up input/output data structures at the upper levels of the protocol.
2. The linked-in function looks for a valid address at location 205 by reading the contents of vector 190 to find the exception handler stack and offsetting to the entry point pointer 205. If the entry point vector 205 does not store a valid address but instead the "no library available" value, then the host is assumed to be disconnected. An appropriate error code is then produced.
3. If the address is valid, it is assumed to be that of the library entry point. A call is made to that entry point and the code at this address will determine whether the host is connected and whether input/output is enabled. The method of checking the library code is described later herein. If the code checks indicate either that no host is connected, or that input/output is not enabled, an appropriate error code will be determined stating the reason for input/output failure.
4. If the host is connected and input/output is enabled, the application will communicate with the debugger to carry out the input output operation and return an appropriate status code.

Referring now to Figure 3, the first application 121 may be initiated by the host computer 1 at an input 131. If the first application 121 needs to input data from the

host computer 1 then it must make use of the dynamic library 30. To do this, application 121 reads the vector 190 and from its contents accesses the address of the exception handler stack 202, offsets to the entry point pointer 205 which results in the entry point into the dynamic link library 30 being supplied to the application at input 141. The application fetches information from the dynamic link library 30 at terminal 151. The application 121 is thus able, by use of the required subroutines in the library 30 to "translate" information coming in over link 101 from the host computer.

If the first application needs to output information to the host computer, then a similar process applies.

Further inspection of Figure 3 shows that the first application 121 is capable of starting the second application 122 over a path 132. If during execution of the second application 122 there is a requirement for the second application to input or output data from or to the host computer 1, the second application uses the vector 190 to load the entry point data from memory location 205 over the path 142 and accesses the library 30 over the path 152. This in turn enables the second application 122 to input or output data as required.

Each of the applications typically comprises a start up code.

The system described uses a single region of memory 202 for the exception handler stack 21. However, where more than one application exists in the embedded system, each may use a different region of memory for the stack of its exception handler. If this occurs, then when a host is connected, a region of memory known to the host must be reserved for this stack and the vector of the target

updated to point to this region. The consequence is that all applications use a single area of stack for the particular exception. This ensures that the host has a single stack area, which it will use for the linker-loader 120 to store the address information of the library 30.

Without these measures being taken, each of the stack regions will be valid for a particular time period and the host will be unable to determine which of these stack regions to write the relevant data to at any one time.

There are three ways in which an application may start. In the first, the host starts the application, in the second the application is started by the target following reset, eg power-up, and in the third, the application is started by another application, referred to here as the initiating application.

For the first, use of the dynamic link library is necessary.

For the second, the application should run correctly without recourse to the library, and if the application tries to call the library, an error should be indicated.

However, for the third, the provision of the dynamic link library depends on how the initiating application was started. If the initiating application was started by the host, then the dynamic link library should be made available: if the initiating application started after target reset, then no library should be needed. (It will of course be understood by those skilled in the art that a whole chain of applications may exist, in which case

the decision depends on how the first in the chain started up).

To cope with the above situation, the embodiment initialises the contents of the entry point pointer 205 according to the following rules: -

If the host has started the application, the application start up code assumes that the entry point pointer value is valid - i.e. the host has set the value stored by the entry point pointer 205 to point to a dynamic library, which the host has downloaded to the target.

If the application has been started following reset of the target, the application start up code will place the above-discussed "no library available" value in entry point pointer 205 indicating that there is no available dynamic library.

If the application has been started by an initialising application then:-

a) If the host started the initialising application, then the value stored by entry point pointer 205 is considered valid and it is considered that there is a valid library in the system.

b) If however there is no host connected, or if the host did not start the initialising application, then it is necessary to reset the contents of 205 to the "no library available" special value.

To implement these rules, the target digital signal processor supports a mechanism whereby the host can set a single bit of state in a register of the target, which is

initialised upon an input to reset logic 123, i.e., a processor reset. This bit is hereinafter referred to as the "host-connected bit" and typically resides in a processor register or a memory-mapped register.

As noted above, two system start-up situations exist:-

1. Ordinary, where the target executes a reset sequence, such as power up, and starts executing code at an address fixed, for example by contents of ROM within the embedded digital signal processor.
2. Via the host, in which case the host controls the reset sequence and may also control the address of the first code to be executed.

If the digital signal processor is reset using the ordinary sequence, the host-connected bit is initialised by the digital signal processor reset-logic. The start up code of the first application to be executed reads the host-connected bit, and because it is initialised determines that the host is regarded as not connected. The code then sets the contents of memory location 205 to the no-library value.

If however the host starts the target, then:-

1. The host resets the target and holds it in a suspended state.
2. The host downloads the exception handler stack and adjusts the vector to point to this stack.
3. The host downloads the input/output library to the target and sets the entry point pointer 205 in the stack to contain the entry-point to this library.

4. The host inverts the host-connected bit.
5. The host releases the target from its suspended state.

Note that the order may differ from the above. For example, the library may be dynamically loaded, whereby the host determines its entry point, and then the stack - containing the entry point pointer set to the entry point - may be dynamically loaded.

In any event, the start up code of the first application then executes, reads the host-connected bit (which has been inverted) and decides that a host is connected. As a result, it is assumed that the host has loaded a library, and correctly set the entry point pointer. Thus the entry point pointer 205 is left unchanged.

The dynamically loaded subroutine is called with two machine-word sized parameters. It returns a machine-word sized value. The first parameter is a value that represents an operation to perform, the second a parameter for that operation. Certain operations do not use the second parameter. Similarly, it is not necessary for an operation to utilise the return value. The application will have been provided at the time of writing, with the values representing the operations anticipated as necessary. These values are then used in calling the relevant subroutine from the library.

Alternatively, the library may include a routine translating the values from the application into different values corresponding to those needed by the library.

One such operation will determine whether the host is connected. This operation will be used by the application by calling the input/output library subroutine with the first parameter containing a reserved value, which represents "host connected operation". The second parameter is not used by this operation so an arbitrary value may be passed. The subroutine will determine whether the host is connected with an internal action and return one of two possible values, which are "host-connected" and "host not connected".

Similar operations are used to send and receive data from the host, and to specify callback functions in the application to be used by the input/output subroutine in special circumstances.

The two-parameter model provides very good backward compatibility to legacy applications, which cannot be changed. For instance, a later dynamic library may provide additional features. Each additional feature may be accessed by using a value of the first parameter that was not available in earlier libraries. Features that were present in older libraries are provided in the newer libraries and each of these will be accessed with the same value for the first parameter in both old and new libraries. The second parameter remains a 'feature-specific' parameter.

Having provided a mechanism for loading a dynamic library onto a remote system, the same approach is useable to satisfy a wide range of run-time requirements, including but not limited to input/output. An example of such a requirement is the need to provide a work round to a hardware bug that becomes manifest during a debug session. Such bugs may only be present on a particular version or revision of the silicon. Once the problem is

discovered, a routine may be written that contains a feature that may be called by the application when appropriate to prevent the bug from occurring, or to mask the bug. This routine may be incorporated within a library on the host, and loaded dynamically into the target at the start of a debug session. Components that do not possess the bug will not require the routine and may be provided with a version of the library that does not have the bug work-around feature. Such a version provides a subset of library functionality such as input/output capability.

In an alternative embodiment shown in Figure 4, a processor register 1190, which is large enough to contain a pointer, is reserved for use by the input/output system. The digital signal processor vector to an exception handler stack and the pointer at a reserved position of the exception handler stack are not necessary. The register is initialised by the application start-up code to contain the "no library available" value if the host is not connected. If the host is connected, the host places a value in this register pointing to the entry point 1204 of IO dynamic library 1300, which the host has loaded onto the target.

When the application wishes to perform input/output, it looks at the value in the reserved register 1190. If this value is not the special 'no library available' value, it is assumed to be the address of the entry point 1204 to the input/output subroutine. The application calls the subroutine at this address to carry out input/output.

CLAIMS:

1. A method of debugging a target system using a host system connected thereto, the target system comprising a digital signal processor having associated memory comprising plural addressable locations, said target system further having a reserved storage location designated as a vector, said memory further storing plural application programs, each application program having respective associated exception handler code, the method comprising:

dynamically loading an stack to said reserved region;

causing the vector of said target system to point to said stack whereby all said applications use the said stack for said exception.

2. The method of claim 1 further comprising the steps of: -

dynamically loading a library to said target from said host whereby said dynamically loaded library has an entry point at one of said plural addressable locations, wherein said library includes at least one routine needed for running at least one of said applications; and

storing information indicative of the address of said one location at a reserved location in said stack.

3. The method of claim 2 further comprising the step of: -

using said host to start of one of said applications, whereby a running application identifies the need for said routine;

reading said vector;

using the contents of the vector to access said stack;

reading said reserved stack location to derive the entry point of said library to said application;

calling said routine from said library.

4. The method of claim 3 wherein said routine comprises a communication routine enabling said host and target to communicate.

5. The method of claim 3 wherein said routine comprises a routine enabling a hardware bug to be worked round.

6. The method of claim 3 wherein said step of calling comprises supplying a first item of data indicative of the routine and a second item of data for the operation to be performed by said routine.

7. The method of claim 6 wherein said routine returns an item of data to said application.

8. The method of claim 6 or 7 wherein each said data item comprises a machine word.

9. A device for debugging a target system, the device comprising a host system connected thereto, the target system comprising a digital signal processor having associated memory comprising plural addressable locations, said target system further having a reserved storage location designated as a vector, said memory further storing plural application programs, each application program having respective associated exception handler code, the device further comprising:

stack dynamic loading circuitry in said host for dynamically loading a stack to said reserved region, whereby said loader comprises an indication of the location in said memory of said stack;

vector writing circuitry receiving said indication, and writing to said the vector of said target system the address of said stack whereby all said applications use the said stack for said exception.

10. The device of claim 9 further comprising: -

a computer file in said host, said file comprising a library having a routine needed by at least one of said applications, e steps of: -

library dynamic loading circuitry for dynamically loading said library to said target from said host whereby said dynamically loaded library has an entry point at one of said plural addressable locations; and

stack writing circuitry for storing information indicative of the address of said one location at a reserved location in said stack.

11. The device of claim 10 further comprising: -

control circuitry in said host for starting one of said applications, whereby a running application identifies the need for said routine;

vector reading circuitry in said target for reading the content of said vector;

addressing circuitry for using the contents of the vector to access said stack;

stack reading circuitry for reading said reserved stack location to derive the entry point of said library to said application;

calling circuitry for calling said routine from said library.

12. The device of claim 11 wherein said calling circuitry is operable to supply a first item of data indicative of the routine and a second item of data for the operation to be performed by said routine.

13. The device of claim 12 wherein each said data item comprises a machine word.




Figure 1




Figure 2




Figure 3




Figure 4